

1-1-2013

Derived and residual Sylvester-Hadamard designs and the Smith normal form

İLHAN HACIOĞLU

Follow this and additional works at: <https://journals.tubitak.gov.tr/math>



Part of the [Mathematics Commons](#)

Recommended Citation

HACIOĞLU, İLHAN (2013) "Derived and residual Sylvester-Hadamard designs and the Smith normal form," *Turkish Journal of Mathematics*: Vol. 37: No. 3, Article 3. <https://doi.org/10.3906/mat-1112-18>
Available at: <https://journals.tubitak.gov.tr/math/vol37/iss3/3>

This Article is brought to you for free and open access by TÜBİTAK Academic Journals. It has been accepted for inclusion in Turkish Journal of Mathematics by an authorized editor of TÜBİTAK Academic Journals. For more information, please contact academic.publications@tubitak.gov.tr.

Derived and residual Sylvester-Hadamard designs and the Smith normal form

İlhan HACIOĞLU*

Çanakkale Onsekiz Mart University, Department of Mathematics, Çanakkale, Turkey

Received: 13.12.2011 • Accepted: 20.03.2012 • Published Online: 26.04.2013 • Printed: 27.05.2013

Abstract: We computed the Smith normal form of Sylvester-Hadamard designs and its complement, their derived and residual Sylvester-Hadamard designs and their complementary derived and residual Sylvester-Hadamard designs.

Key words: Sylvester-Hadamard design, Smith normal form, derived, residual designs

1. Preliminaries

The p -ranks of Sylvester-Hadamard designs play an important role in shift registers and pseudo-noise matrices [1]. In this article by finding the Smith normal form we completely solve this problem, give formulas for their derived and residual Sylvester-Hadamard designs and their complementary derived and residual Sylvester-Hadamard designs.

By a balanced incomplete block design (*BIBD*) with parameters (v, b, r, k, λ) we mean an arrangement of v treatments into b subsets of these treatments called “blocks”, such that

- (i) each block consists of k distinct treatments;
- (ii) each treatment occurs in r different blocks;
- (iii) each pair of distinct treatments occur together in λ different blocks.

The following equations are satisfied by any *BIBD*:

$$vr = bk \quad \text{and} \quad \lambda(v - 1) = r(k - 1)$$

A *BIBD* is said to be symmetric if $v = b$ and in consequence $r = k$. We call such a design a (v, k, λ) design.

Existence of a (v, k, λ) design implies the existence of its derived and residual design with parameters $(k, b - 1, r - 1, \lambda, \lambda - 1)$ and $(v - k, b - 1, r, k - \lambda, \lambda)$, respectively. They are obtained, respectively, by deleting a block of the (v, k, λ) design retaining all the treatments in $b - 1$ blocks that appear (or do not appear) in the deleted block.

If b_1, b_2, \dots, b_v and $B_1, B_2 \dots B_b$ denote the treatments and blocks of the *BIBD* respectively then the incidence matrix $N = (n_{ij})$ of the design is defined by

$$n_{ij} = \begin{cases} 1, & \text{if } b_j \in B_i ; \\ 0, & \text{if } b_j \notin B_i. \end{cases}$$

*Correspondence: hacioglu@comu.edu.tr

If N^T denotes the transpose of N then $N^T N = (r - \lambda)I + \lambda J$, where I is the identity matrix of order v and J is the square matrix of order v with all elements 1.

For any BIBD with incidence matrix N there exists the complementary design with parameters $(v, b, b - r, v - k, b - 2r + \lambda)$ with incidence matrix N^c , which is obtained by interchanging 0 and 1 in N .

Integral Equivalence: If A and B are matrices over the ring \mathbb{Z} of integers, A and B are called *equivalent* ($A \sim B$) if there are \mathbb{Z} -matrices P and Q , of determinant ± 1 , such that

$$B = PAQ,$$

which means that one can be obtained from the other by a sequence of the following operations:

- Reorder the rows,
- Negate some row,
- Add an integer multiple of one row to another,

and the corresponding column operations.

Note: In the next section we use block \mathbb{Z} -equivalent row or column operations.

Smith Normal Form: If A is any n by n \mathbb{Z} -matrix, then there is a unique \mathbb{Z} -matrix

$$D = \text{diag}(a_1, a_2, \dots, a_n)$$

such that $A \sim D$ and

$$a_1 | a_2 | \dots | a_r, a_{r+1} = \dots = a_n = 0,$$

where the a_i are non-negative. The a_i are called *invariants factors* of A and D is the Smith normal form ($SNF(A)$) of A .

A *Hadamard matrix* H of order m is an m by m matrix with elements ± 1 such that $HH^T = mI_m$. A *Sylvester-Hadamard matrix* of order 2^m is a Hadamard matrix that can be partitioned into

$$\begin{bmatrix} H & H \\ H & -H \end{bmatrix}, \tag{1}$$

where $H_1 = \begin{bmatrix} 1 \\ 1 \end{bmatrix}$, $H_2 = \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix}$ and

$$H_{2^m} = \begin{bmatrix} H_{2^{m-1}} & H_{2^{m-1}} \\ H_{2^{m-1}} & -H_{2^{m-1}} \end{bmatrix} = H_2 \otimes H_{2^{m-1}} \text{ for } 2 \leq m \in \mathbb{N} \text{ where } \otimes \text{ denotes the Kronecker product.}$$

2. Sylvester-Hadamard Matrix

We have the following theorem from [3] that gives us the Smith normal of the matrix defined in (1).

Theorem 1. Let H denote the Sylvester-Hadamard matrix of order 2^m . Then the Smith normal form of H is

$$\text{diag}[\underbrace{1, 2, \dots, 2}_{C(m,1)}, \underbrace{4, \dots, 4}_{C(m,2)}, \underbrace{8, \dots, 8}_{C(m,3)}, \dots, \underbrace{2^{m-1}, \dots, 2^{m-1}}_{C(m,m-1)}, 2^m]$$

where $C(m, k)$ denotes the binomial coefficients.

Without loss of generality, assume that H is of the form in (1). Then if we multiply row 1 with -1 and add row 1 to all other rows, and then subtract column 1 from all other columns, we see that H is integrally equivalent to the direct sum $[1] \oplus (-2A) = [1] \oplus (2A)$, where A is the incidence matrix of Sylvester-Hadamard $(2^m - 1, 2^{m-1}, 2^{m-2})$ -design. Since we have the direct sum we can state immediately the following theorem.

3. Sylvester-Hadamard Designs

Theorem 1 *Let A denote the incidence matrix of the Sylvester-Hadamard $(2^m - 1, 2^{m-1}, 2^{m-2})$ -design. Then the Smith normal form of A is*

$$diag[\underbrace{1, \dots, 1}_{C(m,1)}, \underbrace{2, \dots, 2}_{C(m,2)}, \underbrace{4, \dots, 4}_{C(m,3)}, \dots, \underbrace{2^{m-2}, \dots, 2^{m-2}}_{C(m,m-1)}, 2^{m-1}]$$

4. Complementary Sylvester-Hadamard Designs

Before computing the Smith normal form of the Complementary Sylvester-Hadamard $(2^m - 1, 2^{m-1} - 1, 2^{m-2} - 1)$ -design we need the following two results from [2].

Theorem 2 *Let A be the incidence matrix for a (v, k, λ) design with k and λ relatively prime and $n = k - \lambda$. Then $a_1 = a_2 = 1$, $a_i = n/a_{v-i+2}$ for $3 \leq i \leq v - i$, $a_v = nk$.*

Corollary 3 *Suppose that $n = p^t, p$ a prime. Let n_j be the number of invariant factors of A equal to p^j , $0 \leq j \leq t$. Then*

$$n_0 = n_t + 2, \quad n_j = n_{t-j}, \quad 1 \leq j \leq t - 1.$$

Now we state the theorem.

Theorem 4 *Let A denote the incidence matrix of the Complementary Sylvester-Hadamard $(2^m - 1, 2^{m-1} - 1, 2^{m-2} - 1)$ -design. Then the Smith normal form of A is*

$$diag[\underbrace{1, \dots, 1}_{C(m,1)+1}, \underbrace{2, \dots, 2}_{C(m,2)}, \underbrace{4, \dots, 4}_{C(m,3)}, \dots, \underbrace{2^{m-2}, \dots, 2^{m-2}}_{C(m,m-1)-1}, 2^{m-2}(2^{m-1} - 1)]$$

Proof Since the parameters of our design satisfy the conditions of theorem 3 we get the last term $a_v = nk = (2^{m-1} - 1 - 2^{m-2} + 1)(2^{m-1} - 1) = 2^{m-2}(2^{m-1} - 1)$. By using the determinant of this design and corollary 1 we get the rest of the terms in the Smith normal form. \square

5. Derived and Residual Sylvester-Hadamard Designs

Theorem 5 *Let N_1 denote the incidence matrix of the derived design of the Sylvester-Hadamard $(2^{m+1} - 1, 2^m, 2^{m-1})$ -design. Then the Smith normal form of N_1 is of the form $SNF(N_1) = [D_1|0]$ where*

$$D_1 = diag \left[\underbrace{1, \dots, 1}_{C(m,1)+1}, \underbrace{2, \dots, 2}_{C(m,2)}, \underbrace{4, \dots, 4}_{C(m,3)}, \dots, \underbrace{2^{m-2}, \dots, 2^{m-2}}_{C(m,m-1)}, 2^{m-1} \right]$$

Theorem 6 Let N_0 denote the the incidence matrix of residual design of the Sylvester-Hadamard $(2^{m+1} - 1, 2^m, 2^{m-1})$ -design. Then the Smith normal form of N_0 is of the form $SNF(N_0) = [D_0|0]$, where

$$D_0 = \text{diag} \left[\underbrace{1, \dots, 1}_{C(m,1)}, \underbrace{2, \dots, 2}_{C(m,2)}, \underbrace{4, \dots, 4}_{C(m,3)}, \dots, \underbrace{2^{m-2}, \dots, 2^{m-2}}_{C(m,m-1)}, 2^{m-1} \right].$$

Proof Since Sylvester-Hadamard design is transitive on points and on blocks, the incidence matrix of the Sylvester-Hadamard $(2^{m+1} - 1, 2^m, 2^{m-1})$ -design can be put in the form

$$\left[\begin{array}{c|c|c} A & \underline{0} & A \\ \hline \underline{0} & \underline{1} & \underline{1} \\ \hline A & \underline{1} & A^c \end{array} \right],$$

where A is the incidence matrix of the Sylvester-Hadamard $(2^m - 1, 2^{m-1}, 2^{m-2})$ -design, A^c the complementary design of A , $\underline{0}, \underline{1}$ are the column or row vectors of appropriate size with all 1's and all 0's, respectively, and $\mathbf{0}$ is the appropriate size of the zero matrix. So the derived design takes the form

$$\left[\begin{array}{c|c} \underline{0} & \underline{1} \\ \hline A & A^c \end{array} \right].$$

and the residual design takes the form

$$[A \mid A].$$

We compute the SNF of the derived design by doing the following \mathbb{Z} -equivalent block operations:

1. Add the first block column to the second block column.
2. Then multiply the first row by -1 and add it to every other row.
3. Then swap the first block column and the second one.
4. Multiply the first column by -1 and add to every column in the first block.
5. Swap the second and the third column.

Namely, the operations we did are as follows:

$$\begin{aligned} & \left[\begin{array}{c|c} \underline{0} & \underline{1} \\ \hline A & A^c \end{array} \right] \longrightarrow \left[\begin{array}{c|c} \underline{0} & \underline{1} \\ \hline A & A^c + A \end{array} \right] = \left[\begin{array}{c|c} \underline{0} & \underline{1} \\ \hline A & J \end{array} \right] \longrightarrow \left[\begin{array}{c|c} \underline{0} & \underline{1} \\ \hline A & \mathbf{0} \end{array} \right] \longrightarrow \\ & \left[\begin{array}{c|c} \underline{1} & \underline{0} \\ \hline \mathbf{0} & A \end{array} \right] \longrightarrow \left[\begin{array}{c|c} \underline{1} & \mathbf{0} \\ \hline \underline{0} & A \end{array} \right] \longrightarrow \left[\begin{array}{c|c} \underline{1} & \underline{0} \\ \hline \underline{0} & A \end{array} \right] \longrightarrow \left[\begin{array}{c|c} \underline{1} & \underline{0} \\ \hline \underline{0} & SNF(A) \end{array} \right]. \end{aligned}$$

Now the result for the derived design follows by theorem 2. Similarly, if we multiply the first column block by -1 and add it to the second block column we get

$$[A \mid A] \longrightarrow [A \mid \mathbf{0}] \longrightarrow [SNF(A) \mid \mathbf{0}],$$

and the result for the residual design follows by theorem 2. □

6. Derived and Residual Complementary Sylvester-Hadamard Designs

Theorem 7 Let N_1^c denote the incidence matrix of the derived design of the complementary Sylvester-Hadamard $(2^{m+1} - 1, 2^m - 1, 2^{m-1} - 1)$ -design. Then the Smith normal form of N_1^c is of the form $SNF(N_1^c) = [D_1^c|0]$, where

$$D_1^c = \text{diag} \left[\underbrace{1, \dots, 1}_{C(m,1)+1}, \underbrace{2, \dots, 2}_{C(m,2)}, \underbrace{4, \dots, 4}_{C(m,3)}, \dots, \underbrace{2^{m-2}, \dots, 2^{m-2}}_{C(m,m-1)-1}, 2^{m-2}(2^{m-1} - 1) \right].$$

Theorem 8 Let N_0^c denote the incidence matrix of the residual design of the complementary Sylvester-Hadamard $(2^{m+1} - 1, 2^m - 1, 2^{m-1} - 1)$ -design. Then the Smith normal form of N_0^c is of the form $SNF(N_0^c) = [D_0^c|0]$, where

$$D_0^c = \text{diag} \left[\underbrace{1, \dots, 1}_{C(m,1)+1}, \underbrace{2, \dots, 2}_{C(m,2)}, \underbrace{4, \dots, 4}_{C(m,3)}, \dots, \underbrace{2^{m-2}, \dots, 2^{m-2}}_{C(m,m-1)}, 2^{m-1} \right].$$

Proof The incidence matrix of the complementary Sylvester-Hadamard $(2^{m+1} - 1, 2^m - 1, 2^{m-1} - 1)$ -design can be put in the form

$$\left[\begin{array}{c|c|c} B & \underline{1} & B \\ \hline \underline{1} & 0 & \underline{0} \\ \hline B & \underline{0} & A \end{array} \right],$$

where $B = A^c$ is the incidence matrix of the complementary Sylvester-Hadamard $(2^m - 1, 2^{m-1} - 1, 2^{m-2} - 1)$ -design. So the derived design takes the form

$$[B \mid B].$$

and the residual design takes the form

$$\left[\begin{array}{c|c} \underline{1} & \underline{0} \\ \hline B & A \end{array} \right]$$

We compute the SNF of the derived design by doing similar \mathbb{Z} -equivalent block operations described in the proof of theorem 6. Namely,

$$[B \mid B] \longrightarrow [B \mid 0] \longrightarrow [SNF(B) \mid 0].$$

Now the result for the derived design follows from theorem 4. Similarly,

$$\begin{aligned} & \left[\begin{array}{c|c} \underline{1} & \underline{0} \\ \hline B & A \end{array} \right] \longrightarrow \left[\begin{array}{c|c} \underline{1} & \underline{0} \\ \hline B+A & A \end{array} \right] \longrightarrow \left[\begin{array}{c|c} \underline{1} & \underline{0} \\ \hline J & A \end{array} \right] \longrightarrow \left[\begin{array}{c|c} \underline{1} & \underline{0} \\ \hline \underline{0} & A \end{array} \right] \\ & \longrightarrow \left[\begin{array}{c|c|c} \underline{1} & \underline{0} & \underline{0} \\ \hline \underline{0} & \underline{0} & A \end{array} \right] \longrightarrow \left[\begin{array}{c|c|c} \underline{1} & \underline{0} & \underline{0} \\ \hline \underline{0} & A & \underline{0} \end{array} \right] \longrightarrow \left[\begin{array}{c|c|c} \underline{1} & \underline{0} & \underline{0} \\ \hline \underline{0} & SNF(A) & \underline{0} \end{array} \right] \end{aligned}$$

and the result follows from theorem 2. □

References

- [1] Bella, T., Olshevsky, V. and Sakhnovich, L.: Ranks of Hadamard matrices and equivalence of Sylvester Hadamard and pseudo-noise matrices, *Operator Theory: Advances and Applications*, 1, 1–13, (2007).
- [2] Deretsky, Z.: On the symmetry of the Smith normal form for (v, k, λ) designs, *Linear and Multilinear Algebra*, 14, 187–193, (1983).
- [3] Wallis, W.D.: *Combinatorial Designs*, Marcel Dekker, New York, (1988).